

PFRS - SERVICE POST CONNECTOR WITH LAG SCREW

PFRS-35-2C

Description

Purpose: Connection with COPPERSTEEL or copper cables. Used to align one or two downconductors on building facades (masonry or concrete). Use with nylon bushing S-10.

Characteristics: Tightening connection. High electrical conductivity and corrosion resistance.

Application: Grounding systems in general e lightning protection systems.

Material: Copper alloy.

Application Tool: Box open-ended or monkey wrenches.



Datasheet

Material	-
Qty. Of Conductors	2
Conductors - Cross Section (mm ²)	
Minimum	6 - 6
Maximum	35 - 35
Dimensions (mm)	
Figure	2
L	20,6
A	63,5
D	30,5
Pigtail - R	1/4* SOBERBA
Package	
Qty. / Package	60
Unit Weight (g)	50,60